



3-in-1 Foldable Wireless Desk Charger

TLL151331

User guide



INTO YOUR FUTURE

Thank you, for choosing Tellur!


Please, read this user manual carefully before using the product and keep it safe for future references.

Note!


To ensure charging 3 devices safely and efficiently, you must use a 9V/2A adapter (QUALCOMM Quick Charger 2.0 or 3.0) and a quick charge cable (if not use the appropriate adapter and quick charge cable, the charger may not charge your phone, or may not charge 2 devices simultaneously or may even damage the charger).


Product Appearance

1. Wireless charge area, for Phone
2. Non-slip material
3. LED intelligent light



4. Wireless charge area, for TWS earphone
5. Wireless charge magnetically area, for Apple Watch
6. Type-C port





- 7. Non-slip material
- 8. Radiating holes area
- 9. Product tag

Product description

The 3-in-1 Foldable Wireless Desk Charger, a compact charging house, powered from only one outlet, can charge 3 devices simultaneously. When you need to charge your smartphone, Apple watches and your Air Pods 2 or Air Pods Pro, or some other TWS earphones, just put them on and the wireless charging will automatically start. All this, will make your desk clean and tidy and also, make your life easier. The charger is so space-saving designed to help you integrate your smartphone and life, very well, especially for Apple users. The sleek, modern design is complemented by a bright light slit, indicating the state of charge.

The phone can be positioned for charging, both horizontally and vertically.

The foldable charger is designed to slim and compact, easy to carry, perfect for traveling.


The material of the 3 in 1 wireless charger is of high quality, with a smooth texture, pleasant to the touch, which ensures adhesion and protects against scratches.

The entire system protects the connected devices against overheating and overvoltage, maintaining a normal temperature during charging.



The Magnetic Wireless Charging Zone for the Apple Watch can be used in two positions.

Operation steps

1. Connect the wireless charger 3 in 1, to a 9V/2A QC3.0 adapter through a type-C quick charge cable, to switch on the power.
2. Place your smartphone on the destined wireless charge area
3. Place the Apple Watch on the magnetic charging area, to charge it
4. Place your earphone case on the destined wireless charge area.



Charging diagram



LED light instructions

● Green lights on – Standby mode for smartphone Wireless charging (the phone is not placed in the wireless charging zone).

● Blue light is on – Wireless charging the smartphone (the phone is placed in the wireless charging zone).

●● Blue and Green light flash – A foreign body is detected, or the phone is misaligned (the phone charging will automatically stop).

Compatible devices

I. Smart Phone

1. Apple: iPhone 13, iPhone 13 mini, iPhone 13 Pro, iPhone 13 Pro Max, iPhone 12, iPhone 12 Mini, iPhone 12 Pro, iPhone 12 Pro Max, iPhone 11, iPhone 11 Pro, iPhone 11 Pro Max, iPhone X, iPhone XS, iPhone XS Max, iPhone XR, iPhone 8, iPhone 8 Plus.
2. Samsung Galaxy S: 21 5G, 21+ 5G, 21 Ultra 5G, FE 5G, 20 5G, 20+5G, 20 Ultra 5G, 10, 10+, 10e, 9, 9*, 8, 8+, 7, 7 edge, 6, 6 edge, 6 edge+6 G9209, 6Active; Galaxy Note: 10, 10e, 10+, 9, 8, 7, 6, 5.
3. LG: G2 (VS980, Verizon version), G3, G6, G6+, G7, G7 ThinQ, G7+ ThinQ, G8, G8ThinQ, V30+/35, V40 Thin Q, V50 Thin Q, LG Lucid2 (VS870), LG Optimus F5 (As870), LG Optimus Vu3, Spectrum 2, Optimus G Pro, Optimus Vull, Optimus LTE 2, etc.
4. Motorola: Droid Turbo, Droid Turbo 2, Droid 5, Moto Maxx, Ultra M, Moto X Force.
5. HUAWEI: P50, P50 Pro, Mate 40 Pro, Mate 40 Pro+, Mate 40 RS, Mate 30, Mate 30 RS, Mate 30 Pro, Mate 30E Pro, P40 Pro, P40 Pro+, P30 Pro, Mate 20 Pro, Mate RS.
6. Xiaomi: 11 Ultra, 11 Pro, 11, 10s, MIX4, 10, 10 Pro, 9, 9 Pro, 9X, MIX 3, MIX 2S.

Including other devices with wireless charging receiver built-in; other some devices need to add a wireless charging receiver.

Note: All devices must meet the Qi standard.

II. Smart Watch

Apple: iWatch S1, S2, S3, S4, S5, S6, S7, SE.

III. TWS Bluetooth earphones

Apple Air Pods 2, Apple Air Pods 3, Apple Air Pods Pro,

Samsung Galaxy Buds/Buds+/Buds Pro/Buds Live.

Huawei Freebuds2/3/4i/Pro; and more TWS (with wireless charging case).

Technical specifications

Input: 9V/2A, 9V/2.7A, 12V/2A

Input port: Type-C

Smartphone output: 15W(Max), 10W, 7.5W, 5W

Air Pods 2/3/Pro output: 3W

Apple Watch output: 2.5W

Total output: 20.5W (Max)

Cable length: 1 meter (Type-C, 3A)

Charging coils: 2

Charging conversion rate: >73%

Transmission distance (phone): ≤8mm

Material: ABS

Safety protections: Overvoltage protection, temperature control and foreign object detection

Color: Black

Size: 169x74x20mm

Weight: 170g

Accessories List

- 1x Wireless Charger 3 in 1
- 1x Type-C quick charge cable, 1m
- 1x User manual

Attention!

1. Please, keep the charger away from water or other liquids.
2. If you need to clean the charger, please, make sure it is not connected to the power supply.
3. Environment temperature for use: 0 -45 °C

Troubleshooting

1. If you're experiencing interrupted or slow charging, check the following:
 - The back of your phone should not have any metal, pop sockets or credit cards
 - Place the phone in the center of the charging surface (this lets the charging coil in your phone line up with the one inside the wireless charger)
 - Phone case should not be thicker than 5 mm for effective charging
2. If you're failing to charge your device, please, try out the following:
 - Please, restart your cellphone and test with other USB cable
 - Please, check whether the indicator turns on or not
 - Please, check if the Adapter is QC3.0 Quick Charger (Output 9V/2A) or not. iPhone original adapter does not match with the wireless charger.
 - Please, check your phone case thickness ($\leq 5\text{mm}$). Metal ring or magnetic pad will not be available.
3. If you're using the recommended wireless charger with the QC3.0 adapter and have removed any potential charging obstructions, but are still experiencing issues, try:
 - Replacing the cable connecting your wireless charger with the power supply.
 - Rebooting your phone.
 - Unplug the adapter and reinsert it.

Disposal and recycling information



The crossed-out wheeled-bin symbol on your product, battery, literature or packaging reminds you that all electronic products and batteries must be taken to separate waste collection points at the end of their working lives; they must not be disposed of in the normal waste stream with household garbage. It is the responsibility of the user to dispose of the equipment using a designated collection point or service for separate recycling of waste electrical and electronic equipment (WEEE) and batteries according to local laws. Proper collection and recycling of your equipment helps ensure EEE waste is recycled in a manner that conserves valuable materials and protects human health and the environment, improper handling, accidental breakage, damage, and/or improper recycling at the end of its life may be harmful for health and environment.