



**User Manual
Power Delivery
(PD) Wall Charger
TLL151271**



INTO YOUR FUTURE

Technical Specifications

- Input: 100-240V; 50/60HZ
- Type-C output (PD 3.0):
5V-3A, 9V-3A, 12V-2.5A, 15V-2A (30W)
- USB output (QC3.0): 5V-3A, 9V-2A, 12V-1.5 (18W)
- Total output: 6A
Total power: 48W
- Features: US, EU and UK plug adapter
- Protection functions: Short circuit, overcurrent, overvoltage, overtemperature
- Size: 65x61x29mm
- Weight: 131g
- Available colors: Black
- Compatible PD devices: Macbook Air 2018, iPad Pro 12.9", iPad Pro 10.5", iPad Pro 11", iPhone 11/ 11 Pro/ 11 Max/ XR/ X/ XS Max/ XS/ 8 Plus/ 8, Samsung S20 Ultra/ S20+ /S20, Samsung S10+/ S10/ S10e, Google Pixel 4 XL/ 4/ 3a XL/ 3a/ 3 XL/ 3"

Instructions

1. Plug the charger into your wall socket.
2. Connect one end of your charging cable to your device's charging port (smartphone, power bank, portable speaker, etc.)
3. Connect the other end to the USB or Type-C port on the charger.
4. Unplug your device when fully charged.

Disposal and recycling information



The crossed-out wheeled-bin symbol on your product, battery, literature or packaging reminds

you that all electronic products and batteries must be taken to separate waste collection points at the end of their working lives; they must not be disposed of in the normal waste stream with household garbage.

It is the responsibility of the user to dispose of the equipment using a designated collection point or service for separate recycling of waste electrical and electronic equipment (WEEE) and batteries according to local laws.

Proper collection and recycling of your equipment helps ensure EEE waste is recycled in a manner that conserves valuable materials and protects human health and the environment, improper handling, accidental breakage, damage, and/or improper recycling at the end of its life may be harmful for health and environment.



ABN Systems International



Str. Marinariilor, nr.29
Sector 1, Bucuresti, Romania



004.021.233.09.95



office@tellur.com
office@abnsystems.ro



www.tellur.com